

How to upgrade the firmware in Safe mode.

Unlike previous model, M6500/7000 supports Safe Upgrade from USB device. In case of local HDD and USB devices are connected at the same time, TViX will check USB device first.

Au choix entre les 2 méthodes :

1. Safe upgrade mode by connecting the USB

Copy firmware file(fwp) to the root folder of your USB device.

Connect your USB to the TViX.

Power “ON” the TViX kit by simultaneously pressing the “SETUP” button on the TViX.

“SAFE UPGRADE” will be displayed on the VFD of the TViX.

If the TViX found firmware files, the version of copied firmware will be displayed on the VFD screen. For example, if the firmware version is 1.1.0, you will see 'HDD1/FW 1:01:00'.

If you press the OK button on the remote control or the TViX, it will start the firmware upgrade.

The VFD will show PRE when erasing the old firmware.

When upgrading, the VFD, UPG and numbers will be displayed.

The TViX will automatically reboot after the upgrade has been successfully finished.

2. Safe upgrade mode for the HDD.

Connect the TViX to your PC with a USB and then turn it on.

Create a tvixfw folder in your primary partition.

Copy the firmware file into the tvixfw folder of the TViX hard drive.

Detach TViX from your PC after select Safe remove.

After detach, turn off the unit.

Press the SETUP button on the top panel and turn “ON” the TViX HD using power button.

The firmware version of copied file will be displayed on the VFD screen. For example, if the firmware version is 1.1.0, you will see 'HDD1/FW 1:01:00'.

If you press the OK button on the remote control or the TViX, it will start the firmware upgrade.

The VFD will show PRE when erasing the old firmware.

When upgrading, the VFD, UPG and numbers will be displayed.

The TViX will automatically reboot after the upgrade has been successfully finished.